



Pref1/4: da questi menù a tendina e' possibile scegliere quali servers di indirizzamento selezionare e co

Retry timeout: consente di settare il tempo di attesa tra un tentativo e l'altro di connessione al server d'ir


Use Proxy: consente di attivare la modalità del proxy su EchoLink. Grazie all'uso del proxy e' possibile a

Host: qui si dovrà inserire l'indirizzo IP del proxy da contattare per effettuare l'accesso alla rete EchoLink

Port: inserite la porta a cui risponde il proxy. Nel caso di proxy pubblici la porta e' la "8100".

Password: inserite la password da usare per accedere al proxy. Nel caso di proxy pubblici la password e

Automatically dial conn: questo settaggio consente di effettuare la chiamata telefonica per accedere ad




Connect attempt: questo parametro setta il tempo massimo per il tentativo di connessione, prima che il s


Transmit time limit: questo parametro setta il tempo massimo per cui EchoLink consentira' una trasmissi


Receive time limit: setta il limite massimo che EchoLink consentira' ad una trasmissione sul lato Internet


Inactivity timeout: questo timer serve a fissare un tempo limite di inattivita' per il quale una connessione


Receive hang time: questo timer specifica per quanto tempo EchoLink rimarra' in modo ricevente nel mo


System Setup
My Station
Servers
Timing
Audio
Input Device:
ESS Maestro
Output Device:
ESS Maestro
Mic Type:
Open in Full Duplex
Auto Sample Rate Compensation
300 Hz TX High-Pass Filter
Recording Mode:
No Recording
Folder...
Network Buffering
20
PC Buffering
7
Min
Max
Total audio delay:
2.16 s
Reset to Defaults
OK
Annulla
?


Preferences
List
Connections
Security
Signals
Update station list automatically
Update every 300 sec
Even while connected
Show in Index View
Repeaters (-R)
Links (-L)
Users
Conference Servers
Stations Busy
Stations Free
Alarmed Only
Show Alarms in pop-up window
Add new QSOs to Favorites
Restore window size and position on startup
Show icons in pull-down menus
OK
Annulla
?


Preferences
List
Connections
Security
Signals
Conferencing
Allow conferences
Limit to 2 other stations
Update Location entry with status
Send station list to all stations
Allow multi-conferencing
Location/Description
Free: Quartu Sant'Elena
Busy: Quartu Sant'Elena
Show name of connected conference
PTT Control...
Station Information File: info.txt
Choose...
Show Alert when "Doubling"
Edit...
OK
Annulla
?


Preferences
List
Connections
Security
Signals
Accept conns from:
Repeaters (-R)
Links (-L)
Users
Conferences
Dynamic conf detect
Accept only these calls:
Deny these calls:
Add New
Remove
Remove All
International Prefixes
Accept
Deny
Afghanistan
Albania
Algeria
Andorra
Angola
Antigua-Barbuda
>>
<<
Apply security settings to:
Inbound connection requests
Outbound connection attempts
OK
Annulla
?


Preferences
List
Connections
Security
Signals
Configure signals (sounds) for the following events:
Connected
Disconnected
Alarm
Over
Text Msg
None
Default
Custom
The settings on this page apply to Single User Mode only. To configure Signals for Sysop mode, please use the Signals tab under Tools-->Sysop Settings.
OK
Annulla
?